


HIGH PRECISION VOLTAGE REGULATOR


- INPUT VOLTAGE UP TO 40V
- OUTPUT VOLTAGE ADJUSTABLE FROM 2 TO 37V
- POSITIVE OR NEGATIVE SUPPLY OPERATION
- SERIES, SHUNT, SWITCHING OR FLOATING OPERATION
- OUTPUT CURRENT TO 150mA WITHOUT EXTERNAL PASS TRANSISTOR
- ADJUSTABLE CURRENT LIMITING



DESCRIPTION

The LM723 is a monolithic integrated programmable voltage regulator, assembled in 14-lead dual in-line plastic and ceramic package, 10-lead Metal Can (TO-100 type) and SO-14 micropackage. The circuit provides internal current limiting. When the output current exceeds 150mA an external NPN or PNP pass element may be used. Provisions are made for adjustable current limiting and remote shut-down.

BLOCK DIAGRAM





ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	LM723	LM723C	Unit
V_i	Input Voltage	40	40	V
ΔV_{i-o}	Dropout Voltage	40	40	V
I_o	Output Current	150	150	mA
I_{ref}	Current from V_{ref}	15	25	mA
T_{op}	Operating Temperature	-55 to 125	0 to 70	°C
T_{stg}	Storage Temperature	-65 to 150	-65 to 150	°C
T_j	Junction Temperature	150	125	°C

THERMAL DATA

Symbol	Parameter	Plastic DIP-14	Ceramic DIP-14	TO-100	SO-14	Unit
$R_{th j-amb}$	Thermal Resistance Junction-ambient	Max	200	150	155	165 °C/W

PIN CONNECTION (top views)




ORDER CODES

Type	TO-100	Ceramic DIP-14	Plastic DIP-14	SO-14
LM723	LM723H	LM723J		
LM723C	LM723CH	LM723CJ	LM723CN	LM723CD

ELECTRICAL CHARACTERISTICS (refer to the test circuit, $T_{amb} = 25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter	Test Conditions	LM723C			LM723			Unit
			Min.	Typ.	Max.	Min.	Typ.	Max.	
$\frac{\Delta V_o}{\Delta V_i}$	Line Regulation	$V_i = 12 \text{ to } 15V$		0.01	0.1		0.01	0.1	%
		$V_i = 12 \text{ to } 40V$		0.1	0.5		0.02	0.2	
$\frac{\Delta V_o}{V_o}$	Load Regulation	$V_i = 12 \text{ to } 15V ; T_{min} \leq T_{amb} \leq T_{max}$			0.3			0.3	%
		$I_o = 1 \text{ to } 50\text{mA}$		0.03	0.2		0.03	0.15	
$T_{min} \leq T_{amb} \leq T_{max}$		$I_o = 1 \text{ to } 10\text{mA}$			0.6			0.6	
V_{REF}	Reference Voltage	$I_{ref} = 160\mu\text{A}$	6.8	7.15	7.5	6.95	7.15	7.35	V
SVR	Ripple Rejection	$f = 100\text{Hz to } 10\text{KHz}$ $C_{ref} = 0$ $C_{ref} = 5\mu\text{F}$		74 86			74 86		dB dB
$\frac{\Delta V_o}{\Delta T}$	Output Voltage Drift				150			150	ppm $^\circ\text{C}$
I_{SC}	Short Circuit Current Limiting	$R_{SC} = 10\Omega$ $V_o = 0$		65			65		mA
V_i	Input Voltage Range		9.5		40	9.5		40	V
V_o	Output Voltage Range		2		37	2		37	V
$V_i - V_o$			3		38	3		38	V
I_d	Quiescent Drain Current	$I_o = 0$ $V_i = 30V$		2.3	4		2.3	5	mA
KvH	Long Term Stability			0.1			0.1		% 1000 hrs
e_N	Output Noise Voltage	$BW = 100\text{Hz to } 10\text{KHz}$ $C_{ref} = 0$ $C_{ref} = 5\mu\text{F}$		20 2.5			20 2.5		μV μV

Note : $T_{min} = 0^\circ\text{C}$ (LM723C) ; -55°C (LM723).
 $T_{max} = 70^\circ\text{C}$ (LM723C) ; 125°C (LM723).

TEST CIRCUIT (pin configuration relative to the plastic package)

■ 7929237 0051528 649 ■

3/9

527

Figure 1 : Maximum Output Current vs. Voltage Drop.




Figure 2 : Current Limiting Characteristics.




Figure 3 : Current Limiting Characteristics vs. Junction Temperature.




Figure 5 : Load Regulation Characteristics with Current Limiting.




Figure 6 : Load Regulation Characteristics with Current Limiting










Figure 7 : Line Regulation vs. Voltage Drop.**Figure 8 : Load Regulation vs. Voltage Drop.****Figure 9 : Quiescent Drain Current vs. Input Voltage.****Figure 10 : Line Transient Response.****Figure 11 : Load Transient Response.****Figure 12 : Output Impedance vs. Frequency.**

7929237 0051530 2T7

5/9

529

Table 1 : Resistor Values ($\text{K}\Omega$) for Standard Output Voltages.


Output Voltage	Applicable Figures	Fixed Output $\pm 5\%$		Output Adjustable $\pm 10\% (^{\circ})$			Output Voltage	Applicable Figures	Fixed Output $\pm 5\%$		Output Adjustable $\pm 10\% (^{\circ})$		
		R ₁	R ₂	R ₁	P ₁	R ₂			R ₁	R ₂	P ₁	R ₂	
+ 3	13, 16	4.12	3.01	1.8	0.5	1.2	+ 100						
+ 5	13, 16	2.15	4.99	0.75	0.5	2.2	+ 250						
+ 6	13, 16	1.15	6.04	0.5	0.5	2.7	- 6($^{\circ}$)	15	3.57	2.43	1.2	0.5	0.75
+ 9	14, 16	1.87	7.15	0.75	1	2.7	- 9	15	3.48	5.36	1.2	0.5	2
+ 12	14, 16	4.87	7.15	2	1	3	- 12	15	3.57	8.45	1.2	0.5	3.3
+ 15	14, 16	7.87	7.15	3.3	1	3	- 15	15	3.65	11.5	1.2	0.5	4.3
+ 28	14, 16	21	7.15	5.6	1	2	- 28	15	3.57	24.3	1.2	0.5	10

Note : (*) Replace R₁/R₂ divider with the circuit of fig. 24.


(**) V⁺ must be connected to a + 3V or greater supply.

Table 2 : Formulae for Intermediate Output Voltages.



Outputs from + 2 to + 7 Volts Fig. 13, 16 $V_O = [V_{ref} \times \frac{R_2}{R_1 + R_2}]$		Current Limiting $I_{LIMIT} = \frac{V_{SENSE}}{R_{sc}}$
Outputs from + 7 to + 37 Volts Fig. 14, 16, $V_O = [V_{ref} \times \frac{R_1 + R_2}{R_2}]$	Output from - 6 to - 250 Volts Fig. 15, 20 $V_O = [\frac{V_{ref}}{2} \times \frac{R_1 + R_2}{R_1}] ; R_3 = R_4$	Foldback Current Limiting $I_{KNEE} = [\frac{V_O R_3}{R_{sc} R_4} + \frac{V_{SENSE} (R_3 + R_4)}{R_{sc} R_4}]$ $I_{SHORT CKT} = [\frac{V_{SENSE} X}{R_{sc}} \frac{R_3 + R_4}{R_4}]$

APPLICATION INFORMATION (pin numbers relative to the plastic package).**Figure 13 : Basic Low Voltage Regulator**
($V_o = 2$ to $7V$).**Typical performance**

Regulated Output Voltage	5V
Line Regulation ($\Delta V_i = 3V$)	0.5mV
Load Regulation ($\Delta I_o = 50mA$)	1.5mV

Figure 14 : Basic High Voltage Regulator
($V_o = 7$ to $37V$).**Typical performance**


Regulated Output Voltage	15V
Line Regulation ($\Delta V_i = 3V$)	1.5mV
Load Regulation ($\Delta I_o = 50mA$)	4.5mV

Figure 15 : Negative Voltage Regulator.**Figure 16 : Positive Voltage Regulator (external NPN Pass Transistor).**


7929237 0051532 07T

7/9


531

APPLICATION INFORMATION (continued).**Figure 17 : Positive Voltage Regulator (External PNP Pass Transistor)****Typical performance**


Regulated Output Voltage	5V
Line Regulation ($\Delta V_i = 3V$)	0.5mV
Load Regulation ($\Delta I_o = 1 A$)	1.5mV

Figure 18 : Foldback current limiting**Typical performance**


Regulated Output Voltage	5 V
Line Regulation ($\Delta V_i = 3V$)	0.5mV
Load Regulation ($\Delta I_o = 10 mA$)	1mV
Current Limit Knee	20 mA

Figure 19 : Positive Floating Regulator**Typical performance**


Regulated Output Voltage	100 V
Line Regulation ($\Delta V_i = 20V$)	15 mV
Load Regulation ($\Delta I_o = 50mA$)	20 mV

Figure 20 : Negative Floating Regulator**Typical performance**

Regulated Output Voltage	- 100 V
Line Regulation ($\Delta V_i = 20V$)	30 mV
Load Regulation ($\Delta I_o = 100 mA$)	20 mV

APPLICATION INFORMATION (continued).**Figure 21 : Positive Switching Regulator****Typical performance**


Regulated Output Voltage	5 V
Line Regulation ($\Delta V_i = 30$ V).....	10 mV
Load Regulation ($\Delta I_o = 2$ A).....	80 mV

Figure 22 : Remote Shutdown Regulator With Current Limiting

Note: current limit transistor may be used for shutdown if current limiting is not required.

Typical performance

Regulated Output Voltage	5 V
Line Regulation ($\Delta V_i = 3$ V)	0.5 mV
Load Regulation ($\Delta I_o = 50$ mA)	1.5 mV

Figure 23 : Shunt Regulator.**Typical performance**

Regulated Output Voltage.....	5 V
Line Regulation ($\Delta V_i = 10$ V).....	2 mV
Load Regulation ($\Delta I_o = 100$ mA).....	5 mV

Figure 24 : Output Voltage Adjust