

N-Channel JFETs

Switches

ELECTRICAL CHARACTERISTICS at $T_A = 25^\circ\text{C}$

Device Type	$V_{DS(ON)}$		I_{DSS}		$V_{DS(ON)}$				I_{DSS}				C_{iss}^1		C_{oss}^1		$r_{DS(on)}$ Max (Ω)	Pro- cess
					Limits		Conditions		Limits		Conditions							
	Min. (V)	($\pm I_D$) (μA)	Max. (nA)	($\pm V_{GS}$) (V)	Min (V)	Max. (V)	V_{GS} (V)	I_D (nA)	Min (mA)	Max (mA)	($\pm V_{GS}$) (V)		Max (pF)	($\pm V_{GS}$) (V)	Max (pF)	($\pm V_{GS}$) (V)		
2N3824	-50	-1.0	-0.1	-30	—	-8.0	15	1.0	—	—	—		6.0	15	3.0	-8.0 ²	250	NJ32
2N3966	-30	-1.0	-0.1	-20	-4.0	-6.0	10	10	2.0	—	20		6.0	20	1.5	-7.0 ²	220	NJ32
2N3970	-40	-1.0	-0.3	-20	-4.0	-10	20	1.0	50	150	20		25	20	6.0	-12 ²	30	NJ132
2N3971	-40	-1.0	-0.3	-20	-2.0	-5.0	20	1.0	25	75	20		25	20	6.0	-12 ²	60	NJ132
2N3972	-40	-1.0	-0.3	-20	-0.5	-3.0	20	1.0	5.0	30	20		25	20	6.0	-12 ²	100	NJ132
2N4091	-40	-1.0	-0.5	-20	-5.0	-10	20	1.0	30	—	20		16	20	5.0	-20 ²	30	NJ132
2N4092	-40	-1.0	-0.5	-20	-2.0	-7.0	20	1.0	15	—	20		16	20	5.0	-20 ²	50	NJ132
2N4093	-40	-1.0	-0.5	-20	-1.0	-5.0	20	1.0	8.0	—	20		16	20	5.0	-20 ²	80	NJ132
2N4391	-40	-1.0	-0.1	-20	-4.0	-10	20	1.0	50	150	20		16	20	5.0	-12 ²	30	NJ132
2N4392	-40	-1.0	-0.1	-20	-2.0	-5.0	20	1.0	25	75	20		16	20	5.0	-7.0 ²	60	NJ132
2N4393	-40	-1.0	-0.1	-20	-0.5	-3.0	20	1.0	5.0	30	20		16	20	5.0	-5.0 ²	100	NJ132
2N4856	-40	-1.0	-0.25	-20	-4.0	-10	15	1.0	50	—	15		18	-10 ²	8.0	-10 ²	25	NJ132
2N4856A	-40	-1.0	-0.25	-20	-4.0	-10	15	1.0	50	—	15		10	-10 ²	4.0	-10 ²	25	NJ132
2N4857	-40	-1.0	-0.25	-20	-2.0	-6.0	15	1.0	20	100	15		18	-10 ²	8.0	-10 ²	40	NJ132
2N4857A	-40	-1.0	-0.25	-20	-2.0	-6.0	15	1.0	20	100	15		10	-10 ²	3.5	-10 ²	40	NJ132
2N4858	-40	-1.0	-0.25	-20	-0.8	-4.0	15	1.0	8.0	80	15		18	-10 ²	8.0	-10 ²	40	NJ132
2N4858A	-40	-1.0	-0.25	-20	-0.8	-4.0	15	1.0	8.0	80	15		10	-10 ²	3.5	-10 ²	60	NJ132
2N4859	-30	-1.0	-0.25	-15	-4.0	-10	15	1.0	50	—	15		18	-10 ²	8.0	-10 ²	25	NJ132
2N4859A	-30	-1.0	-0.25	-15	-4.0	-10	15	1.0	50	—	15		10	-10 ²	4.0	-10 ²	25	NJ132
2N4860	-30	-1.0	-0.25	-15	-2.0	-6.0	15	1.0	20	100	15		18	-10 ²	8.0	-10 ²	40	NJ132
2N4860A	-30	-1.0	-0.25	-15	-2.0	-6.0	15	1.0	20	100	15		10	-10 ²	3.5	-10 ²	40	NJ132
2N4861	-30	-1.0	-0.5	-15	-0.8	-4.0	15	1.0	8.0	80	15		18	-10 ²	8.0	-10 ²	60	NJ132
2N4861A	-30	-1.0	-0.5	-15	-0.8	-4.0	15	1.0	8.0	80	15		10	-10 ²	3.5	-10 ²	60	NJ132
2N5432	-25	-1.0	-0.2	-15	-4.0	-10	5.0	3.0	150	—	15		30	-10 ²	15	-10 ²	5.0	NJ903
2N5433	-25	-1.0	-0.2	-15	-3.0	-9.0	5.0	3.0	100	—	15		30	-10 ²	15	-10 ²	7.0	NJ903
2N5434	-25	-1.0	-0.2	-15	-1.0	-4.0	5.0	3.0	30	—	15		30	-10 ²	15	-10 ²	10	NJ903

NOTES
1) $V_{GS} = 0\text{ V}$
2) I_D in μA
3) $V_{GS} = 0\text{ V}$, V_{DS} in volts

RF Amplifiers

ELECTRICAL CHARACTERISTICS at $T_A = 25^\circ\text{C}$

Device Type	$V_{DS(ON)}$		I_{DSS}		$V_{DS(ON)}$				I_{DSS}				G_m		C_{iss}^1		C_{oss}^1		$r_{DS(on)}$ Max (Ω)	Process	
					Limits		Conditions														
	Min (V)	($\pm I_D$) (μA)	Max (nA)	($\pm V_{GS}$) (V)	Min (V)	Max (V)	V_{GS} (V)	I_D (nA)	Min (mA)	Max (mA)	($\pm V_{GS}$) (V)		Min (mS)	Max (mS)	($\pm V_{GS}$) (V)	Max (pF)	($\pm V_{GS}$) (V)	Max (pF)	($\pm V_{GS}$) (V)		
2N3823	-30	-1.0	-0.5	-20	—	-8.0	10	1.0	4.0	20	15		3.5	6.5	15	6.0	15	2.0	15	—	NJ32
2N4223	-30	-1.0	-0.25	-20	—	-8.0	15	1.0	3.0	18	15		3.0	7.0	15	6.0	15	2.0	15	—	NJ32
2N4224	-30	-1.0	-0.5	-20	—	-8.0	15	1.0	2.0	20	15		2.0	7.5	15	6.0	15	2.0	15	—	NJ32
2N4416	-30	-1.0	-0.1	-20	—	-6.0	15	1.0	5.0	15	15		4.5	7.5	15	4.0	15	0.8	15	—	NJ26
2N4416A	-35	-1.0	-0.1	-20	-2.5	-6.0	15	1.0	5.0	15	15		4.5	7.5	15	4.0	15	0.8	15	—	NJ26
2N5078	-30	-1.0	-0.25	-20	-0.5	-8.0	15	1.0	4.0	25	15		4.0	—	15	6.0	15	2.0	15	—	NJ26
2N5367	-25	-1.0	-0.1	-15	-1.0	-6.0	10	1.0	10	30	10		6.0	10	10 ²	5.0	10 ²	1.2	10 ²	—	NJ26A
2N5368	-25	-1.0	-0.1	-15	-1.0	-6.0	10	1.0	5.0	40	10		6.5	10	10	6.5	10	1.3	10	—	NJ26A

NOTES
1) $V_{GS} = 0\text{ V}$
2) $I_D = 10\text{ μA}$

Copyright © Each Manufacturing Company.

All Datasheets cannot be modified without permission.

This datasheet has been download from :

www.AllDataSheet.com

100% Free DataSheet Search Site.

Free Download.

No Register.

Fast Search System.

www.AllDataSheet.com