

# W&T-AD06XXX

## 6W 系列電源適配器

### 產品輸出規格

3.7V	4.2V	5.0V	5.0V	5.0V	6.0V	6.0V	7.2V	8.0V	9.0V	9.0V	12.0V	12.0V
1.0A	1.0A	150A	500MA	1.0A	500MA	800MA	0.5A	500MA	500MA	800MA	350MA	500MA
50MV	50MV	50MV	50mV	50mV	50mV	50mV	50mV	50mV	80mV	80mV	100mV	100mV

### 輸入/輸出規格(INPUT/OUTPUT SPECIFICATIONS):

- 輸入電壓(INPUT VOLTAGE): 100V-240V AC, 50/60Hz
- 輸入電壓範圍(RANGE VOLTAGE): 90V-264V AC, 47-63Hz
- 輸出功率(OUTPUT POWER): 6W
- 輸出電壓(OUTPUT VOLTAGE): DC 5.0V ~ 24.0V
- 過壓保護(OVER VOLTAGE PROTECTION): 120%min
- 過流保護(OVER CURRENT PROTECTION): 120%min
- 短路保護(SHORT PROTECTION): AUTO RECOVERY
- 輸出電壓變動(LOAD REGULATION):  $\pm 5\%$

### 常規參數(GENERAL SPECIFICATIONS):

- 工作環境溫度(OPERATING TEMPERATURE): 0 ~ 40°C
- 儲存溫度(STORAGE TEMPERATURE): -20 ~ 85°C
- 工作濕度(OPERATING RELATIVE HUMIDITY): 5 ~ 95% RH
- 耐壓(WITHSTANDING VOLTAGE): AC 3000V(min), 5ma(max).
- 絕緣阻抗(INSULATION RESISTANCE): DC 500V 100M $\Omega$  (min)

### 安規(SAFETY):

PSE UL CE GS EK FCC

### 用途(APPLICATION):

- 任何攜帶型設備或機器(ANY PORTABLE DEVICE OR MACHINE)
- 測試設備(TESTER MACHINE)
- 通訊終端設備(COMMUNICATION TERMINALS)

.....